## PRODUCT DATASHEET

# NiMH Battery Charger (CH2PC4)

**EMEA Region** 

**Download Instructions (multilingual)** 



#### **SAFETY TIMER**

• Ensures charger is not active for extended periods of time



### **Mini Charger**



Before Using Your Charger: Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*® NiMH batteries.

#### Product Detail:

Designation:	Mini Charge	er	
Model:	CH2PC4		
Color:	olor: Black		
Charge Capability:	arge Capability: "AA" (1) or (2)		
	"AAA" (1) or (2)		
Note: Do not charge (1) "AA" and (1) "AAA"			
at the same time. Please refer to the			
	instructions for orientation diagram.		
Charging Times:	Battery	Capacity	Estimated
(estimated)	(NiMH)	(mAh)	(time)
	AA	1300-2000	7-10 hrs
	AA	2000-2300	10-12 hrs
	AAA	500-800	5-8 hrs
Shutoff Mechanism:	Timer (15 hours)		
Charging Current:	"AA" 170-200mA		
	"AAA" 80-100mA		
Trickle Charge: None			
Input Rating:	: 100-240VAC, 50/60Hz, 3W		
Typical Weight:	t: 65 grams		
Dimensions (mm):	115 x 45 x 70 (L x W x H)		
Safety Features:	Safety Features: Reverse Polarity Protection		
	Safety Timer to Prevent Overcharge		

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication. Contents herein do not constitute a warranty.

